



Adressierung

X8:4 X8:3 X8:2 X8:1 | Adressbereich
 X9:4 X9:3 X9:2 X9:1 |

Speichersperrsignal

X6:1 X6:2 X6:3 | Signal
 X7:1 X7:2 X7:3 |

-	-	-	-	0000-0FFF
-	-	-	x	1000-1FFF
-	-	x	-	2000-2FFF
-	-	x	x	3000-3FFF
-	x	-	-	4000-4FFF
-	x	-	x	5000-5FFF
-	x	x	-	6000-6FFF
-	x	x	x	7000-7FFF
x	-	-	-	8000-8FFF
x	-	-	x	9000-9FFF
x	-	x	-	A000-AFFF
x	-	x	x	B000-BFFF
x	x	-	-	C000-CFFF
x	x	-	x	D000-DFFF
x	x	x	-	E000-EFFF
x	x	x	x	F000-FFFF

x	-	-	MEMDI
-	x	-	MEMDI1
-	-	x	MEMDI2

WAIT-Bildung

X10:3-X11:3 | Signal

-	WAIT
x	kein WAIT

Betriebsspannungszufuehrung

X10:2-X11:2 | Signal

x	aus 5 P
-	aus 5 PG